



USER INSTRUCTIONS

Reach Pole Hook MK3

Code

LSYNRP HOOK MK3

CE EN 362:2004 Class A and T

UK
CA EN 362:2004 Class A and T

www.lyon.co.uk/downloads



For more detailed user information and to download a PDF copy of these instructions follow the link above or scan the QR code with your smart phone.

Lyon Equipment Limited,
Units 3-7, Tebay Business Park,
Cumbria,
CA10 3SS,
United Kingdom

Tel: +44 (0) 15396 24040
Email: info@lyon.co.uk
Web: www.lyon.co.uk

© Lyon Equipment Limited 2022



5 055835 618550 >

This information to be read and kept for the lifetime of the product in conjunction with the Lyon Reach Pole Instructions, Pick Off Rescue Kit Instructions, General User Instructions and the connector User Instructions.

Warning

This Hook is for the Lyon MK3 Reach Pole only.

Never use the Reach Pole with an alternative connector. Use only the Lyon approved Hook.

Function

The Reach Pole Hook (hereafter described as 'Hook') is a spare part for the Lyon Reach Pole.

It must only be used with the following products, for the specific operations described in the respective user instructions:

Lyon Reach Pole (product code LSYNRP MK3 or LSYNRP NARU3)

Lyon Pick Off Rescue Kit (product code beginning LSYNPRK)

Lyon NARU Recovery Pack System (product code beginning LNARU RPS)

It must not be used in any other system or assembly or in conjunction with any other product for any other purpose.

All other uses of this product are forbidden without written approval from Lyon Equipment Limited.

Use

Remove the Reach Pole (not supplied) from its transport bag.

Check the serial number on the Reach Pole and obtain its inspection records from your files.

Inspect the Bracket and Reach Pole for any damage or defect that would require its removal from service (see 'Inspection' in the user instructions supplied with the Reach Pole).

If the Bracket and Reach Pole are in an acceptable condition, place the Hook into the Bracket and ensure the tangs on the Hook locate correctly in the Bracket without undue force. Ensure the Hook is securely engaged in the Bracket. Ensure that the Hook releases smoothly from the Reach Pole. Refer to the user instructions provided with the Reach Pole.

If the Hook does not engage or disengage correctly, do not use the Reach Pole and/or Hook, and contact Lyon Equipment for advice.

Amend the Reach Pole inspection record to indicate the fitment of a replacement Hook.

Inspection

The Hook should be subject to:

- Pre-use checks
- Thorough inspections (at least once every 6 months)
- Interim inspections (as appropriate)

The checks should be undertaken in good light. Any item showing any defect should be withdrawn from service immediately.

If in any doubt as to the condition of the product, it should be withdrawn from use immediately and not used again unless confirmed by a competent person that it is acceptable to do so.

It is recommended the Hook is marked with the date of the next or last inspection.

Check that any labels and markings are still intact and readable.

The Hook and any accessories should be checked for signs of overloading, correct functioning, damage, including wear, corrosion, cracking, abrasion or deformity - list not exhaustive. Refer to the connector instructions supplied with the Hook.

Markings

Refer to the connector instructions supplied with the Hook.

End of document

Lyon Product Inspection Record						
Product code	Product description		Year of manufacture	Purchase date		
Length if applicable	Individual serial number		Date of first use		Certificate of conformity number	
Manufacturer Lyon Equipment Limited	Address Unit 3-7 Tebay Business Park Gimble, CA10 3SS United Kingdom		Tel: +44 (0)15396 24040 Email: info@lyon.co.uk Website: www.lyon.co.uk		Other relevant information	
Record of inspection and repair						
Date	Comments	Name and signature of competent inspector			Next due date	
All user instructions supplied with this product must be kept as part of the product inspection record						

EN



General User Instructions

Lyon Equipment Limited,
Units 3-7, Tebay Business Park,
Cumbria,
CA10 3SS
United Kingdom

Tel: +44 (0) 15396 24040
Email: info@lyon.co.uk
Web: www.lyon.co.uk

© Lyon Equipment Limited 2024

www.lyon.co.uk/downloads

For more detailed user
information and to
download a PDF copy of
these instructions and a
Declaration of Conformity
follow the link above or
scan the QR code with
your smart phone



Approved Body controlling manufacture (where applicable)

Where items of Personal Protective Equipment require a UKCA type examination in accordance with Personal Protective Equipment (EU) Regulation 2016/425 on personal protective equipment as brought into GB Law and amended. The body controlling the manufacture is:

Approved Body N° 0120
SGS United Kingdom Limited
Rossmore Business Park,
Inward Way,
Ellesmere Port, Cheshire
CH65 3EN, United Kingdom

Notified Body controlling manufacture (where applicable)

Where items of Personal Protective Equipment require an EU type examination in accordance with Personal Protective Equipment (EU) Regulation 2016/425. The body controlling the manufacture is:

Notified Body N° 0598
SGS Fimko OY
Takomotie 8
FI-00380 HELSINKI, Finland.

WARNING

Make sure that you have read and understood these instructions before using this equipment. These user instructions are to be read and kept along with any other user information provided.

Activities at height are hazardous and may lead to injury or death. It is the user's responsibility, at all times, to ensure that they understand the correct use of any equipment supplied by or through Lyon Equipment Limited, use it only for the purposes for which it is designed, and practice proper safety procedures including having a rescue plan in case of emergency.

This product must not be used outside its limitations, or for any purpose other than those described in the user instructions. Misuses forbidden in these instructions are examples only; many other misuses may exist which could lead to injury or death.

Do not use combinations of items of equipment in which the safe function of any one item is affected or interferes with the safe function of another.

Please note, the information in these user instructions is not exhaustive, and is not a substitute for comprehensive instruction and training by a competent person.

Lyon Equipment Limited is not responsible for any consequences, whether direct, indirect or accidental, resulting from the use of its products. If you are unsure about the correct use of this product, please contact us.

Who can use this equipment

This equipment should only be used by trained, competent and responsible persons, or the user should be under the direct supervision of a trained, competent and responsible person.

Activities at height should not be undertaken by persons affected by alcohol or drug dependence, diabetes, epilepsy, fits, blackouts, fear of heights, vertigo / dizziness / difficulty with balance, heart disease / chest pain, high or low blood pressure, impaired limb function, obesity, psychiatric illness, musculoskeletal issues, e.g. a bad back.

General instructions for use

Equipment must be checked before each use, to ensure it is serviceable and operates correctly. Checks should also be carried out during use. In addition, a thorough inspection by a competent inspector should be carried out in strict accordance with these user instructions, and a record kept of these inspections.

This product may be used with any compatible item of equipment, keeping in mind the limitations of each item in the safety chain. It should be noted that a full body harness is the only type of harness which may be used in a fall arrest system.

The anchor device or anchor point is of primary importance and should be unquestionably reliable. It should be strong enough to withstand the foreseeable maximum load that could be applied e.g. in the event of a fall.

When selecting an anchor, the anticipated directions of loading and potential loads should be taken into account.

Anchors should be selected and positioned to allow work to be carried out in such a way as to minimise the potential for a fall and potential fall distance, for example by keeping the anchor point / device above the user.

Anchors should not have sharp or rough edges which could damage equipment (use edge protection if necessary).

On each occasion of use, verify the free space required beneath the user in order to avoid an impact. Always try to place protection so that any fall will be stopped before the user hits the ground or any other obstruction. Remember to allow for rope stretch and slippage in the belay device or rope ascender / descender. In a fall arrest situation, the user must be protected from dynamic forces of greater than 6 kN in the event of a fall, e.g. by use of a fall arrest system incorporating an (BS) EN 355 energy absorber.

Note to resellers

If the product is resold within the EU, the reseller is responsible for providing instructions for use, maintenance, periodic examination and for repair in the language of the country in which the product is to be used.

If you require the Intrastat commodity code / customs tariff code or NATO stock number (where applicable) for this product, please contact us via www.lyon.co.uk

Maintaining your equipment

Wash in clean water not exceeding 30°C with pure soap and rinse in clean cold water. Do not use chemical products, solvents or detergents – these should be regarded as harmful.

Due to the difficulties in effectively disinfecting equipment, we recommend that any contaminated equipment should be withdrawn from use and disposed of in a suitable manner.

Equipment must be clean and dry before storing. Always allow to dry naturally, away from direct heat. Equipment should be stored in a cool, dry, well-ventilated area, away from excessive heat, high humidity, sharp edges, corrosives, sunlight or other sources of ultraviolet light (UV) and other possible causes of damage.

During transport, this product should be protected from abrasion, mechanical damage, chemical contamination, UV and heat.

Textiles

Always keep textile items at temperatures between -30°C and +50°C.

Metal items

Always keep metal items at temperatures between -20°C and +60°C.

No alterations, additions or repairs may be made to this product without the manufacturer's prior written consent; if done, the repair must be carried out by a competent person for repair authorised by Lyon Equipment Limited to make the repair, and in accordance with specified procedures.

These instructions must be strictly adhered to.

Inspection

A thorough inspection should be carried out at least every 6 months by a competent inspector in accordance with these user instructions. A record of these checks should be kept with the product along with these user instructions. In addition, interim inspections should be carried out where products are used intensively, or in particularly harsh environments where damage is more likely to occur, or where legislation or the type of equipment make it necessary.

Pre-use and thorough inspections are essential because the user's level of protection depends on the continuing correct performance of this product.

PPE (Personal Protective Equipment) inspection training is available from Lyon Equipment Limited.

Lifetime, and when to withdraw your equipment from use

Withdraw your equipment from use if any one of the following applies:

- It shows sign of wear and tear / damage that may affect performance
- Markings on the product are no longer legible
- You suspect it may have been exposed to chemical contamination or extreme temperatures
- It fails a periodic examination
- It has been used to arrest a fall or has been excessively loaded
- It is more than 10 years after the date of manufacture (textile items or items with textile components). Metal items have a potentially indefinite lifespan if stored correctly.
- If you have any reason to doubt that it is safe to use.

It is the responsibility of the competent inspector to decide whether the equipment should be put back into use, or permanently withdrawn from use. Equipment permanently withdrawn from use must be destroyed, and should be recycled where facilities exist.

Certain environmental elements will considerably accelerate wear: salt, sand, dust, snow, ice, moisture, chemicals, sunlight (UV radiation) – list not exhaustive.

Warning: the safe working life of this product may be as short as its first use in extreme circumstances.

If in doubt, do not hesitate to scrap this product.

Guarantee

In the event of any defect in materials or workmanship please return the product to the dealer, distributor or manufacturer within 3 years of purchase for inspection. We will replace or repair as required. This guarantee does not cover normal wear and tear or accidental damage.











Inspection records

A record must be kept for each component, subsystem and system, including name and contact details of the manufacturer or supplier, product description, serial number, year of manufacture, date of purchase, date of first use, any other relevant information, and history of periodic examinations and repairs, the name and signature of the competent inspector and the next due date for inspection. An example of a suitable equipment record is shown on this user instruction and can also be downloaded at www.lyon.co.uk

Local jurisdiction may dictate that extra information be recorded in the inspection record – check your country's legal requirements. Some products may have features which need special monitoring during periodic inspections, e.g. wear indicators, in which case this information should also be recorded on the inspection record.

This page deliberately left blank

Explanation of symbols

	Refer to user instructions
	Permitted use
	Caution
	Danger of death
	Anchor point
	Rope diameter
	Cable
	Load
	Manufacturer details
	Month and year of manufacture. The first two digits give the month of manufacture, the last four give the year.

Additional symbols may be used.

See specific product instruction for explanations

